

BOOSTER

Based on FORTIN AMPLIFICATION 33 Booster - FREDRIK THORDENDAL SIGNATURE

The 66 Boost level control provides up to +22dB of level with added side remote 1/4" jack for channel switching with mini slide switch to change orientation normally open or closed

The 66 Booster is a Clean Booster effects pedal for Electric Guitar . With a level boost of up to 22dB, the 66 transforms any Guitar Amp into a brute high-gain wrecking ball without distorting its sound character. A practical detail of the 66 Booster is the side-mounted channel-switching jack, which can be used to change the channel of the amplifier when the pedal is turned on.

FORTIN 33 Booster



Power supply
negative pole inside
9 V DC

Signal Output

Boost

Signal Input

Channel selection
Connect the channel of Amplifier

Boost on/off or
Channel Switch Latch

Channel Switch
which can be used to change
the channel of the amplifier when the
pedal is turned on

**Boost**

Up to +22 dB boost transform any amplifier into a metal machine
Additional side 6.35 mm jack for channel switching.

Control: Boost

Switch: Channel Switch Latch

LED: effect on

Footswitch: Effect Bypass

Input: 6.35 mm jack

Output: 6.35 mm jack

Channel Switch: 6.35 mm jack

Power connection: coaxial connector 5.5 x 2.1 mm,
negative pole inside

Current consumption: 27 mA

Input Impedance: 5MΩ

Output Impedance: 3kΩ

True Bypass

Power supply : 9 V DC power supply (not included)

Dimensions (W x D x H): 60 x 115 x 32 mm

Weight: 280 g

Internal

Design By USA