Zhuna high current DC power supply

Based On Strymon Zuma Power

INDEPENDENT OUTPUT & ISOLATED GROUND

Getting Started



Connect the included IEC cable to Zhuna and plug the other end into an AC power outlet. Zhuna operates worldwide (120V, 240V, 100V) with the appropriate IEC cable.

Connect Your Pedals

A total of nine high or low-current pedals can be connected to Zhuna. Additional outputs can be added by connecting a other famous brand (Strymon Ojai or Cioks etc) to the 24V OUT jack.

PEDAL OUTPUTS: Connect up to nine effects pedals with the included 5.5mm x 2.1mm pedal cables. Each output is dual-isolated for noisefree operation.

Zhuna will power most effects pedals on the market, including all Demonfx,Strymon etc pedals. Check with each pedal manufacturer for recommended voltage, polarity, and required current. For pedals that have unique power requirements (more than 500mA of current, other voltages such as 24V), you can find configuration details here: www.demon-fx.com



LED INDICATOR:
Each output features an LED indicator. LED illuminates green when a pedal cable is plugged in. LED will turn off if cable is unplugged, or the current draw on the output exceeds the maximum amount available.

9V OUTPUTS:
Seven outputs provide 9V DC, center negative polarity, each with 500mA of available current.

ADJUSTABLE OUTPUTS:
Two outputs provide selectable 9V, 12V, or 18V DC, each with center negative polarity. Each output provides 500mA of available current at 9V, 375mA at 12V, and 250mA at 18V.

24V DC OUT:
Connect a other famous brand power(Strymon and CIOKS etc) to the 24V DC OUT jack and gain additional outputs for your pedals.

Designed By USA

Zhuna
high current DC power supply

Zhuna is Expandable

Is your pedalboard growing? Gain more outputs by linking other famous brand power such as Strymon Ojai and CIOKS 4/CRUX Expander, Eventide PowerMini units to the 24V OUT jack. Zhuna is part of a truly expandable, modular power distribution system that can grow with your pedalboard.



Features

- 9 high-current, fully isolated outputs
- 9 outputs offer 9V DC option
- 500mA per 9V DC output powers nearly any pedal
- 2 selectable outputs offer 9V, 12V, or 18V DC options
- 12V option provides 375mA, 18V provides 250mA
- 9 pedal cables included (5.5mm x 2.1mm barrel connectors, center negative, right angle to straight cables)
- Detachable IEC power cable included
- 24V OUT jack allows connection to additional outputs other brand power supply.

TECHNOLOGY

- Nine individual custom transformers (one per channel) deliver clean, consistent power
- Worldwide power compatibility ensures no-hassle international touring
- Energy efficient, compact design

CONSTRUCTION

- Lightweight and rugged anodized midnight blue aluminum chassis
- Fits under most pedalboards

SPECIFICATIONS

- dimensions 6.8” x 3.3” x 1.8” (173mm x 84mm x 46mm)
- weight 1.25 lbs. (680g)
- Input 100-240V AC 50/60Hz
- 9V DC Outputs Seven (5) 9V DC, 500mA, center-negative
- Adjustable Outputs Two (2) Selectable 9V DC (500mA), 12V DC (375mA), or 18V DC (250mA) center-negative

Designed in USA